

Software Information Sheet



JCM American Corporation
 Japan Cash Machine Germany GmbH
 JCM Gold (H.K.) Ltd.
 JCM United Kingdom Ltd.
 Japan Cash Machine Co., Ltd. (Headquarters – Japan)

TEL +1-702-651-0000
 TEL +49-211-530645-0
 TEL +852-2429-7187
 TEL +44-870-770-2863
 TEL +81-6-6703-8405

General Information

Model Name:	EBA-21-PBH			SW. Req. No.:	G08-087			
SW. Name:	EBA-21(CZE4)-PBH ID-0A2			Date: (dd.mm.yyyy)	10.07.2008	Rev:	A1	
SW. Version:	V4.04-00			Note:				
Country (Code):	Czech Republic (CZE)			Guide:	None			
Currency:	Koruna			Check Sum:	5550			
Direction:	4 Ways			CRC (seed= 0000):	0231			
Denomination:	Denomination	Printed	Issued	MRI#	Denomination	Printed	Issued	MRI#
Years & MRI III/IV.2007	50	'94		CZK50.1	1000	'96		CZK1,000.1B
Ident #	100	'93	'93	CZK100.1A	1000	'08		
64/65th Edition	100	'95~'97		CZK100.1	2000	'96	'96	CZK2,000.1A
	200	'93	'93	CZK200.1A	2000	'99		CZK2,000.1B
	200	'96~'98		CZK200.1	2000	'07		
	500	'95~'97		CZK500.1				
Acceptance Rate:	No less than 90%							
Security level:	Low							
EPROM:	2Mbit, 90 nano-second data access or faster. ST Part M27C2001-90 or equivalent.							
Modifications:	V4.03-00 -> V4.04-00							
Validation:	Acceptance for 1000 ('08) Korun added.							
Operation:								
Interface:								
Memo:								

Dip Switch Settings

#	Dip Switch	
1	OFF	Normal operation mode
	ON	Test and adjustment mode
	(SW-8)	
		OFF Parallel mode
2	OFF	Non escrow mode
	ON	Escrow mode
3	OFF	Not assigned
	ON	Not assigned
4	OFF	Not assigned
	ON	Not assigned
5	OFF	Acceptor only
	ON	With PBH Unit
6	OFF	Not assigned
	ON	Use for "ENABEL/DISABLE Denomination Setting (*)"
7	OFF	Not assigned
	ON	Not assigned
8	OFF	Parallel mode
	ON	Pulse mode

ID-0A2 Data Settings specification

Vend signal (Bill identification signal)


Parallel mode (SW=8 OFF)

Denomination	Vend 1	Vend 2	Vend 3
Waiting	Hi	Hi	Hi
100	Lo	Hi	Hi
200	Hi	Lo	Hi
500	Lo	Lo	Hi
1000	Hi	Hi	Lo
50	Lo	Hi	Lo
2000	Hi	Lo	Lo
Operating	Lo	Lo	Lo

Pulse mode (SW=8 ON) No. of pulse setting

SW-4	No. of pulse ==> Vend 1
OFF	50 Koruna / pulse
ON	10 Koruna / pulse

Directions



(*) ENABEL/DISABLE Denomination Setting Mode

1. Power up the acceptor at normal operation (Pulse or Parallel).
2. Set DipSw 6 = ON in the standby mode (condition LED will turn on).
3. Set Enable or Disable
 Enable Denomination DipSw 7 = OFF.
 Disable Denomination DipSw 7 = ON.
4. Insert the required banknote.
 Acceptor rejects the bill
 When Enable Denomination Setting --> Reject with condition LED OFF
 When Disable Denomination Setting --> Reject with condition LED Signalled
 When validation was not good --> Reject with condition LED ON
6. For another banknote repeat from procedure 3 on.
7. If Setting is completed, set DipSw 6 = OFF
8. Acceptor returns to standby mode and the setup is completed.